

## How do I connect the printer and my computer via Mentation MT580P Bluetooth Thermal Printer (Windows 10)

Follow the steps below:

1. Please install MT580P Driver

Download link:

MT580P Windows Driver.exe

2. From the Start menu, click [Settings] - [Device] - [Bluetooth and other devices].



3. Click [Add Bluetooth or other device].

Settings		– @ ×
က် Home	Bluetooth & other devices	
Find a setting	+ Add Bluetooth or other device	Turn on Bluetooth even faster To turn Bluetooth on or off without opening Settings, open action center and select the Bluetooth icon.
m Bluetooth & other devices	Bluetooth On Now discoverable as "DESKTOP-OEJ44AI"	Related settings Devices and printers
<ul> <li>Mouse</li> <li>Touchpad</li> </ul>	Audio Samsung Level U Paired	Sound settings Display settings More Bluetooth options
፼ Typing ♂ Pen & Windows Ink	Other devices	Send or receive files via Bluetooth
<ul><li>AutoPlay</li><li>USB</li></ul>	Driver is unavailable     Show notifications to connect using Swift Pair     When selected, you can connect to supported Bluetooth devices quickly	Have a question? Sharing files over Bluetooth Reinstalling Bluetooth drivers Fixing Bluetooth connections
	when they're close by and in pairing mode.	Get help



## 4. Select MT580P

## Open [Devices and Printers].



Right-click the printer icon, and select [Properties].

5. Open the [Service] tab, and note the port name ("COM" plus a number) at the right of [Serial port (SPP)].

Add a briter Remove device Remove device Devices (2) DESTROP-OEHAA Simsung Level U Printers (10) Any Dek Printer Fx Fx H2ser/et Pro HP Liser/et Pro HP Li		- 🗇	ック Search Devices and	~ 3			nters	I > Devices and Prir	Hardware and Sound	> Control Panel >	Devices and Printers $ \leftarrow \rightarrow - \uparrow \overline{n} $
Devices (2) DESKTOP-OELHAA Samsung Level U Printers (10) Any Desk Printer Fax HP LaserJet Pro HP LaserJet Pro Microsoft XPS Document Writer Microsoft XPS Document Writer HTSOP Properties This Buetooth device offens the following services. To use a Buetooth Services Ser	- (	-							nove device	ld a printer Re	Add a device A
Joint Construction       Joint Con											Devices (2)
Line       Samsung Level U         Printers (10)         Any Desk Printer       Fax         HP LaserJet Pro BYCLmS       Image: Ample Apple										$\cap$	
DESKTOP-OEL44A Samsung Level U Printers (10) AnyDesk Printer Fax HP Laser/et Pro MFP M125-M126 PCLmS HP Laser/et Pro MFP M126nw Microsoft Print MFP M126nw Microsoft											
I       Printers (10)         Image: Service and the service			×	MT580P Properties						Samsung Level U	DESKTOP-OEJ44A
AnyDesk Printer       Fax       HP Laser/Let Pro MFP M125-M125 PCLmS <ul> <li>HP Laser/Let Pro MFP M125nw</li> <li>Microsoft Print to PDF</li> <li>Microsoft XPS Document Writer</li> </ul> Microsoft XPS MTSB0               Microsoft XPS MTSB0               Microsoft XPS MISB0				General Hardware Services Bluetooth							l Printers (10)
AnyDesk Printer       Fax       HP LaserJet Pro MFP M125/M125       Image: Application of the point of			wing services. To use a	This Bluetooth device offers the follow service, select the check box.							Trincers (Toy
AnyDesk Printer Fax HP Laser/et Pro MFP M125nw to PDF Document Writer MIS80P			20115	Bluetooth Services							
AnyDesk Printer Fax. HP LaserJet Pro HP LaserJet Pro Microsoft Print Microsoft XPS MT580P MFP M125-M125 MFP M126nw to PDF Document Writer PCLmS			COMS	j senai pon (srr) ns_srr	a			C.E.	C.E.		
					MT580P	Microsoft XPS Document Writer	Microsoft Print to PDF	HP LaserJet Pro MFP M126nw	HP LaserJet Pro MFP M125-M126	Fax	AnyDesk Printer
									PCENS		
				3							
MT580P Model: Bluetooth Peripheral Device								e	ooth Peripheral Devic er	OP Model: Blue Category: Prin	MT58
Status: Driver is unavailable			Cancel Apply	OK					r is unavailable	Status: Driv	

If you don't find "COM" mentioned on the right hand side of Serial Port.

Please install

MT580P USB to Serial Driver : MT580P USB turn to serial DriverInstaller\_v1.10.0.exe

- 6. Connect the computer and the printer using a USB cable. A message "Device setup complete" appears on the lower right of your computer's screen, and a printer icon appears in [Devices and Printers].
- 7. Right-click the printer (POS58 Printer) icon, and select [Printer Properties].

			conces and Printers
dd a device Ado	d a printer See what's prin	nting Print server properties Remove device	≡ ▼ 😯
Devices (2)			
DESKTOP-OEJ44A I Printers (10)	Samsung Level U		
AnyDesk Printer	Fax HP Lase MFP M12 PCL	HP Lase/Jet Pro HP Lase/Jet Pro MFP M125aw, Get to yOUT ScreenishOls On all yOur devices Whenever you take screenshots, we'll save them to your PC and store them for free online in OneDrive. This way, you can get to them from anywhere, Learn more Remove device	9 er s
		Save to OneDrive Ask me later   No thanks	

	<ul> <li>Control Panel</li> </ul>	<ul> <li>Hardware and Soun</li> </ul>	d → Devices and Pri	nters				~ 0	P Search	n Devices and Printe	:rs
Add a device A Devices (2)	dd a printer Se	e what's printing	Print server propertie	s Remove devic	ce						
DESKTOP-OEJ44A I Printers (10)	Samsung Level U							General Sharing Por	erties is Advanced	Color Management	Security Device Sett
AnyDesk Printer	Fax	HP LaserJet Pro MFP M125-M126	HP LaserJet Pro MFP M126nw	Microsoft Print to PDF	Microsoft XPS Document Writer	MT580P	OneNote for Windows 10	Location:			
		PCLmS						Model: POS Features Color: No Double-sided: No	i8ENG	Paper availabl Printer 58 (48	e: 3mmx1200mm) ^
								Staple: No Speed: Unknown Maximum resolu	tion: 203 dpi	eferences	Print Test Page
S Poss	8 Printer Model Category Status	: POS58ENG : Printer : 0 document(s) in qu	Jeue							ОК	Cancel App
<i>Р</i> Туре	here to search		0	<del>¤</del> 💽 <u>I</u>	<u>a 🖻 </u>	<u>e</u> 🔁	wiii 198		^	• 👛 🖬 🌈 (4))	ENG 15:56 15-11-2020

8. Open the [Port] tab, and select the port name noted in step

9. Click [**OK**] to close the properties dialog box.

dd a device Add a printer See what's printing Print server	properties Remove device		
AnyDesk Printer Fax HP Lasedet Pro PCLmS HP Lasedet Pro HP Lasedet	POSS8 Printer Properties  General Sharing Ports Advanced Color Management Security Device Settings  POSS8 Printer  Print to the following port(s). Documents will print to the first free checked port.  Port Description Printer  CoMM: Serial Port Comfigure Port Enable bidirectional support Enable printer pooling  OK Cancel Apply	POSS8 Printer VVebex Document Loader	
POS58 Printer Model: POS58ENG Category: Printer Status: 0 document(s) in queue			

Please Click "OK"

Please test printer please click.

It may require to allow printer. Click if POP up appears to allow printer Pair "0000" and allow